Alpha 1500 series

Maintenance Table
09/2017

Adjust	Check	Clean	Lubricate	Replace	Update

Parts	Every 300 hrs or whenever possible	750 hrs	1500 hrs	2250 hrs	3000 hrs	3750 hrs	4500 hrs	5250 hrs	6000 hrs	6750 hrs	7500 hrs	8250 hrs	9000 hrs	9750 hrs	10500 hrs	11250 hrs	12000 hrs
Lamp			Adjust		Adjust		Adjust		Adjust		Adjust		Adjust		Adjust		Adjust
Fans	Clean				Replace				Replace				Replace				Replace
Ir/Uv Filter	Clean																
Color Filters	Clean																
Glass gobos	Clean																
Prism/Frost	Clean																
Reflector	Clean																
Lenses	Clean																
Beam 1500 Lens	Clean				Replace				Replace				Replace				Replace
Eletronic Boards	Clean																
Psu/Driver/Ballast	Clean																
Pan/Tilt Belts	Check				Replace				Replace				Replace				Replace
Effects Belts	Check								Replace								Replace
CMY/CTO Belts	Check				Replace				Replace				Replace				Replace
Rails	Lubricate																
Iris	Check				Replace				Replace				Replace				Replace
Profile 1500 Blades	Clean						Replace						Replace				
Dimmer Blades	Check			Replace				Replace				Replace				Replace	
Belts Tightening		Check		Check		Check		Check		Check		Check		Check		Check	
Battery	Check				Replace				Replace				Replace				Replace
Gobo Bearings	Check				Replace				Replace				Replace				Replace
Head/Yoke/Base	Clean																
Firmware	Update																